



## 1500VA 480 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

**\$618.80 CAD**

Single Phase Control Transformer with a capacity of 1500VA, transforming 480 Volts to 240/480 Volts

SKU: CS1500H-L

Categories: [Control Transformers](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

| Volts Rating | A    | B    | C    | Mounting Centres D x E | F    | Mounting Slot |
|--------------|------|------|------|------------------------|------|---------------|
| 25           | 3    | 3    | 2.5  | 2.5                    | 3.33 | 0.25 x 0.625  |
| 30           | 3    | 3    | 2.5  | 2.5                    | 3.33 | 0.25 x 0.625  |
| 100          | 3    | 4    | 2.5  | 2.5                    | 3.75 | 0.25 x 0.625  |
| 150          | 3.75 | 4.25 | 3.33 | 3.25                   | 3.5  | 0.25 x 0.625  |
| 200          | 3.75 | 4.5  | 3.33 | 3.25                   | 3.5  | 0.25 x 0.625  |
| 250          | 3.75 | 5    | 3.33 | 3.25                   | 3.5  | 0.31 x 0.625  |
| 350          | 4.5  | 5    | 3.75 | 3.75                   | 3.75 | 0.31 x 0.625  |
| 500          | 5.25 | 5    | 4.38 | 4.5                    | 3.75 | 0.31 x 0.625  |
| 750          | 5.25 | 5.5  | 4.38 | 4.5                    | 3.75 | 0.31 x 0.625  |
| 1000         | 5.25 | 6.5  | 4.38 | 4.5                    | 3.75 | 0.31 x 0.625  |
| 1500         | 6.75 | 7.25 | 5.5  | 5                      | 4.75 | 0.31 x 0.625  |
| 2000         | 7.5  | 7.5  | 6.25 | 6                      | 5.25 | 0.31 x 0.625  |
| 3000         | 7.5  | 8.75 | 6.25 | 6                      | 5.5  | 0.31 x 0.625  |
| 5000         | 9    | 10   | 8    | 7                      | 8    | 0.44 x 0.625  |



Single Phase Control Transformer with a capacity of 1500VA, transforming 480 Volts to 240/480 Volts



## PRODUCT SPECIFICATIONS

|                            |  |
|----------------------------|--|
| Weight                     | 70 lbs   |
| Phases                     | <a href="#">1</a>  |
| Connection                 | <a href="#">1Ph-CT-SD-SD</a>   |
| Primary Voltage            | <a href="#">480</a>  |
| Primary Max Current        | <a href="#">3.13A</a>  |
| Primary Markings           | <a href="#">H1-H2</a>  |
| Primary Terminals          | <a href="#">Terminals</a>  |
| Secondary Voltage          | <a href="#">240/480</a>  |
| Secondary Max Current      | <a href="#">6.25A</a>  |
| Secondary Markings         | <a href="#">X1-X2-X3-X4</a>  |
| Secondary Terminals        | <a href="#">Terminals</a>  |
| Primary Taps               | <a href="#">N/A</a>  |
| Conductor Material         | <a href="#">Copper</a>   |
| Temperatue Rise            | <a href="#">115°C</a>  |
| Insuation Class            | <a href="#">180°C (Class F)</a>  |
| BIL (Insulation) Level     | <a href="#">10kV</a>   |
| Efficiency (@35% Load) %   | <a href="#">N/A</a>  |
| Impedance Range            | <a href="#">5.0 – 7.0%</a>   |
| Sound (db)                 | <a href="#">40</a>   |
| Enclosure Type             | <a href="#">Core &amp; Coil</a>  |
| Enclosure Size             | <a href="#">See Core &amp; Coil Chart</a>  |
| Finish/Colour              | <a href="#">N/A</a>  |
| Standards & Certifications | <a href="#">CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered</a> |



OFFICIAL QUOTE

1500VA 480 VOLTS TO 240/480  
VOLTS SINGLE PHASE CONTROL  
TRANSFORMER



|                      |                            |
|----------------------|----------------------------|
| VA                   |                            |
| Country/Manufacturer | <a href="#">Canada/RPM</a> |