



## 2000VA 480 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

**\$638.82 CAD**

Single Phase Control Transformer with a capacity of 2000VA, transforming 480 Volts to 120 Volts

SKU: CE2000H-A

Categories: [Control Transformers](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

VA Rating		Overall Dimensions (inches)			Mounting Dimensions (inches)		
	A	B	C		B x E		
25	3	6	3.5	1.375	4.375		
50	3	6	3.5	1.375	4.375		
100	3	6	3.5	1.375	4.375		
150	3.5	6.658	3.13	3.25	5		
200	3.5	6.658	3.13	3.25	5		
250	3.5	6.658	3.13	3.25	5		
350	4.125	6.5	3.75	3.75	7.875		
500	4.875	7	4.38	4.5	5.5		
750	4.875	7	4.38	4.5	5.5		
1000	4.875	7	4.38	4.5	5.5		
1500	5.625	9	5.63	5	7.25		
2000	6.875	9.25	6.25	6	8		
3000	6.875	9.25	6.25	6	8		
5000	8	10.5	9.5	6	9		



Single Phase Control Transformer with a capacity of 2000VA, transforming 480 Volts to 120 Volts



## PRODUCT SPECIFICATIONS

Weight	8 lbs
Phases	<a href="#">1</a>
Connection	<a href="#">1Ph-CT-SS-SU</a>
Primary Voltage	<a href="#">480</a>
Primary Max Current	<a href="#">4.17A</a>
Primary Markings	<a href="#">H1-H2</a>
Primary Terminals	<a href="#">Leads</a>
Secondary Voltage	<a href="#">120</a>
Secondary Max Current	<a href="#">16.67A</a>
Secondary Markings	<a href="#">X1-X2</a>
Secondary Terminals	<a href="#">Leads</a>
Primary Taps	<a href="#">N/A</a>
Conductor Material	<a href="#">Copper</a>
Temperatue Rise	<a href="#">115°C</a>
Insuation Class	<a href="#">180°C (Class F)</a>
BIL (Insulation) Level	<a href="#">10kV</a>
Efficiency (@35% Load) %	<a href="#">N/A</a>
Impedance Range	<a href="#">5.0 – 7.0%</a>
Sound (db)	<a href="#">40</a>
Enclosure Type	<a href="#">Type-1 Indoor</a>
Enclosure Size	<a href="#">See Enclosure Chart</a>
Finish/Colour	<a href="#">Semigloss – Black</a>
Standards & Certifications	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered</a>



OFFICIAL QUOTE  
2000VA 480 VOLTS TO 120 VOLTS  
SINGLE PHASE CONTROL  
TRANSFORMER



VA	
Country/Manufacturer	<a href="#">Canada/RPM</a>