



3000VA 600 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$993.72 CAD


Single Phase Control Transformer with a capacity
of 3000VA, transforming 600 Volts to 240/480
Volts

SKU: CS3000J-L

Categories: [Control Transformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

Volts	Overall Dimensions	Mounting Dimensions
Rating	A B C	D E F
25	3 3 2.5	2.5 2.5 3.33
30	3 3 2.5	2.5 2.5 3.33
100	3 4 2.5	2.5 3 3.75
150	3.75 4.25 3.33	3.25 3.5 4.5
200	3.75 4.5 3.33	3.25 3.5 4.5
250	3.75 5 3.33	3.25 3.5 4.5
350	4.5 5 3.75	3.75 3.75 4.75
500	5.25 5 4.38	4.5 3.75 4.75
750	5.25 5.5 4.38	4.5 3.75 4.75
1000	5.25 6.5 4.38	4.5 3.75 4.75
1500	6.75 7.25 5.63	5 3.75 5.25
2000	7.5 7.5 6.25	5 4.25 5.25
3000	7.5 8.75 6.25	5 5.5 5.25
5000	9 10 8	7 7 8



Single Phase Control Transformer with a capacity of 3000VA, transforming 600 Volts to 240/480 Volts



PRODUCT SPECIFICATIONS

Weight	70 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	600
Primary Max Current	5A
Primary Markings	H1-H2
Primary Terminals	Terminals
Secondary Voltage	240/480
Secondary Max Current	12.5A
Secondary Markings	X1-X2-X3-X4
Secondary Terminals	Terminals
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	115°C
Insuation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	5.0 – 7.0%
Sound (db)	40
Enclosure Type	Core & Coil
Enclosure Size	See Core & Coil Chart
Finish/Colour	N/A
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE

3000VA 600 VOLTS TO 240/480
VOLTS SINGLE PHASE CONTROL
TRANSFORMER



VA	3000
Country/Manufacturer	Canada/RPM