

350VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER





350VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$274.82 CAD

Single Phase Control Transformer with a capacity of 350VA, transforming 600 Volts to 12/24 Volts

SKU: CE350J-Z Categories: <u>Control Transformers</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 350VA, transforming 600 Volts to 12/24 Volts



350VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER



The quote is valid 30 days from 2 June 2025. The price does not include: "Special Features", freight and possible taxes. Disclosing this information to the third party or other supplier may lead to the cancellation of this quote. All other requests please email to sales@transformersource.ca. Printed: September-16-2024.



1

350VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

Weight	12 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	<u>600</u>
Primary Max Current	<u>0.58A</u>
Primary Markings	<u>H1-H2</u>
Primary Terminals	Leads
Secondary Voltage	12/24
Secondary Max Current	<u>29.17A</u>
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	Leads
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	<u>80°C</u>
Insuation Class	<u>130°C (Class B)</u>
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 – 7.0%</u>
Sound (db)	<u>40</u>
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered
VA	350

The quote is valid 30 days from 2 June 2025. The price does not include: "Special Features", freight and possible taxes. Disclosing this information to the third party or other supplier may lead to the cancellation of this quote. All other requests please email to sales@transformersource.ca. Printed: September-16-2024.



350VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER



Country/Manufacturer

Canada/RPM