



## OFFICIAL QUOTE

### 1000KVA 440 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



## 1000KVA 440 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER

**\$26,112.00 CAD**

Three Phase Autotransformer with a capacity of 1000kVA, transforming 440Y Volts to 200Y Volts

**SKU:** RA1000H2-B1

**Categories:** [Autotransformers](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 1000kVA, transforming 440Y Volts to 200Y Volts



## OFFICIAL QUOTE

1000KVA 440 VOLTS TO 200 VOLTS  
THREE PHASE AUTOTRANSFORMER

## PRODUCT SPECIFICATIONS

|                            |                                                                                                      |
|----------------------------|------------------------------------------------------------------------------------------------------|
| Weight                     | 3626 lbs                                                                                             |
| Phases                     | <a href="#">3</a>                                                                                    |
| kVA                        | <a href="#">1000</a>                                                                                 |
| Connection                 | <a href="#">3PhA-NT-1</a>                                                                            |
| Primary Voltage            | <a href="#">440</a>                                                                                  |
| Primary Max Current        | <a href="#">1312.2A</a>                                                                              |
| Primary Markings           | <a href="#">H1-H2-H3</a>                                                                             |
| Primary Terminals          | <a href="#">Pads</a>                                                                                 |
| Secondary Voltage          | <a href="#">200</a>                                                                                  |
| Secondary Max Current      | <a href="#">2886.8A</a>                                                                              |
| Secondary Markings         | <a href="#">X1-X2-X3</a>                                                                             |
| Secondary Terminals        | <a href="#">Pads</a>                                                                                 |
| Primary Taps               | <a href="#">N/A</a>                                                                                  |
| Conductor Material         | <a href="#">Aluminum</a>                                                                             |
| Insulation Class           | <a href="#">220°C (Class H)</a>                                                                      |
| BIL (Insulation) Level     | <a href="#">10kV</a>                                                                                 |
| Efficiency (@35% Load) %   | <a href="#">N/A</a>                                                                                  |
| Impedance Range            | <a href="#">1.5 – 3.5%</a>                                                                           |
| Sound (db)                 | <a href="#">62</a>                                                                                   |
| Enclosure Type             | <a href="#">NEMA 3R Indoor</a>                                                                       |
| Enclosure Size             | <a href="#">E3R-11</a>                                                                               |
| Finish/Colour              | <a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>                                             |
| Standards & Certifications | <a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a> |



## OFFICIAL QUOTE

**1000KVA 440 VOLTS TO 200 VOLTS  
THREE PHASE AUTOTRANSFORMER**



|                             |                            |
|-----------------------------|----------------------------|
| <b>Country/Manufacturer</b> | <a href="#">Canada/RPM</a> |
|-----------------------------|----------------------------|