



The diagram illustrates a chromosome with four pairs of homologous chromosomes. The top row shows chromosomes X1, X2, X3, and X4. The bottom row shows chromosomes H4, H2, H3, and H1. A crossover is indicated between H2 and H3.

## Page: 1



Primary Terminals	<a href="#">#2-14 AWG</a>
Secondary Voltage	<a href="#">600</a>
Secondary Max Current	<a href="#">8.3A</a>
Secondary Markings	<a href="#">H1-H2</a>
Secondary Terminals	<a href="#">#2-14 AWG</a>
Primary Taps	<a href="#">+/- 1 x 5%</a>
Conductor Material	<a href="#">Copper</a>
Insulation Class	<a href="#">220°C</a>
BIL (Insulation) Level	<a href="#">10kV</a>
Impedance	<a href="#">5.5 – 7.0%</a>
Sound (db)	<a href="#">42</a>
Enclosure Type	<a href="#">NEMA 1</a>
Enclosure	<a href="#">E1-2</a>
Finish	<a href="#">Polyster Powder Coat – ANSI/ASA 61 Grey</a>
Standards & Certifications	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a>
Efficiency	<a href="#">N/A</a>