



Categories: [Autotransformer](#)

A diagram showing a horizontal chain of three vertices. The left vertex is labeled H_0 / X_0 , the middle vertex is labeled X_1 , and the right vertex is labeled H_1 . Above the chain, there are three horizontal lines representing a 3D structure. The chain itself is composed of a series of connected semi-circular arcs.

Weight	85 lbs
Phases	1
kVA	15
Connection	1PhA-NT-1
Primary Voltage	480
Primary Max Current	31.3A
Primary Markings	H0-H1



Primary Terminals	#2-14 AWG
Secondary Voltage	240
Secondary Max Current	62.5A
Secondary Markings	X0-X1
Secondary Terminals	#2-14 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C
BIL (Insulation) Level	10kV
Efficiency	N/A
Impedance	2.5 – 4.5%
Sound (db)	42
Enclosure Type	NEMA 3R Indoor
Enclosure	E3R-4
Finish	Polyster Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered