



Categories: [Encapsulated Autotransformer](#)

A diagram of a three-loop Feynman diagram. It consists of a central vertex from which three lines emerge. The top line is a vertical chain of three loops, with external lines labeled H1 and X1 at the top. The bottom-left line is a chain of two loops, with external lines labeled X3 and H3 at the bottom. The bottom-right line is a chain of two loops, with external lines labeled X2 and H2 at the bottom.

Weight	400 lbs
Phases	3
kVA	15
Connection	3PhA-NT-1
Primary Voltage	600



Primary Max Current	14.4A
Primary Markings	H1-H2-H3
Primary Terminals	#2-14 AWG
Secondary Voltage	240
Secondary Max Current	36.1A
Secondary Markings	X1-X2-X3
Secondary Terminals	#2-14 AWG
Primary Taps	N/A
Conductor Material	Copper
Insuation Class	200°C
BIL (Insulation) Level	10kV
Impedance	0.5 – 1.5%
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure	E3R-3PEP-3
Finish	Polyster Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered