


OFFICIAL QUOTE

100VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER





100VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$131.04 CAD


Single Phase Control Transformer with a capacity of 100VA, transforming 600 Volts to 12/24 Volts

SKU: CS100H-Z

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 100VA, transforming 600 Volts to 12/24 Volts



OFFICIAL QUOTE



100VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

Weight	5 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	600
Primary Max Current	<u>0.17A</u>
Primary Markings	H1-H2
Primary Terminals	<u>Terminals</u>
Secondary Voltage	12/24
Secondary Max Current	8.33A
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	<u>Terminals</u>
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	80°C
Insuation Class	130°C (Class B)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 – 7.0%</u>
Sound (db)	40
Enclosure Type	Core & Coil
Enclosure Size	See Core & Coil Chart
Finish/Colour	N/A
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE



100VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	
Country/Manufacturer	Canada/RPM