

25VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER





25VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER


\$134.68 CAD

Single Phase Control Transformer with a capacity of 25VA, transforming 600 Volts to 12/24 Volts

SKU: CE25J-Z Categories: <u>Control Transformers</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 25VA, transforming 600 Volts to 12/24 Volts



25VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER



The quote is valid 30 days from 8 June 2025. The price does not include: "Special Features", freight and possible taxes. Disclosing this information to the third party or other supplier may lead to the cancellation of this quote. All other requests please email to sales@transformersource.ca. Printed: September-16-2024.



25VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER



PRODUCT SPECIFICATIONS

hases	2.3 lbs 1
	1
onnection	
	1Ph-CT-SD-SD
rimary Voltage	<u>600</u>
rimary Max Current	<u>0.04A</u>
rimary Markings	<u>H1-H2</u>
rimary Terminals	Leads
econdary Voltage	<u>12/24</u>
econdary Max Current	2.08A
econdary Markings	<u>X1-X2-X3-X4</u>
econdary Terminals	Leads
rimary Taps	N/A
onductor Material	<u>Copper</u>
emperatue Rise	<u>80°C</u>
suation Class	<u>130°C (Class B)</u>
IL (Insulation) Level	<u>10kV</u>
fficiency (@35% Load) %	N/A
npedance Range	<u>5.0 – 7.0%</u>
ound (db)	<u>40</u>
nclosure Type	Type-1 Indoor
nclosure Size	See Enclosure Chart
landards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered
A	

The quote is valid 30 days from 8 June 2025. The price does not include: "Special Features", freight and possible taxes. Disclosing this information to the third party or other supplier may lead to the cancellation of this quote. All other requests please email to sales@transformersource.ca. Printed: September-16-2024.



25VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER



Country/Manufacturer

Canada/RPM