

OFFICIAL QUOTE

500VA 120/240 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER





500VA 120/240 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER


\$327.60 CAD


Single Phase Control Transformer with a capacity of 500VA, transforming 120/240 Volts to 240/480 Volts

SKU: CS500K-L

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 500VA, transforming 120/240 Volts to 240/480 Volts



OFFICIAL QUOTE



500VA 120/240 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

| Weight | 40 lbs |
|----------------------------|--|
| Phases | 1 |
| Connection | 1Ph-CT-DD-SU |
| Primary Voltage | 120/240 |
| Primary Max Current | 4.17A |
| Primary Markings | <u>X1-X2-X3-X4</u> |
| Primary Terminals | <u>Terminals</u> |
| Secondary Voltage | 240/480 |
| Secondary Max Current | 2.08A |
| Secondary Markings | <u>H1-H2-H3-H4</u> |
| Secondary Terminals | <u>Terminals</u> |
| Primary Taps | N/A |
| Conductor Material | Copper |
| Temperatue Rise | <u>115°C</u> |
| Insuation Class | 180°C (Class F) |
| BIL (Insulation) Level | <u>10kV</u> |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | <u>5.0 - 7.0%</u> |
| Sound (db) | 40 |
| Enclosure Type | Core & Coil |
| Enclosure Size | See Core & Coil Chart |
| Finish/Colour | N/A |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered |



OFFICIAL QUOTE



500VA 120/240 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

| VA | |
|----------------------|------------|
| Country/Manufacturer | Canada/RPM |