



1000KVA 480 VOLTS TO 575 VOLTS THREE PHASE AUTOTRANSFORMER

\$13,611.07 USD

Three Phase Autotransformer with a capacity of
1000kVA, transforming 480Y Volts to 575Y Volts

SKU: RA1000H-J1

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 1000kVA, transforming 480Y Volts to 575Y Volts



PRODUCT SPECIFICATIONS

Weight	1088 lbs
Phases	3
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	480
Primary Max Current	1202.8A
Primary Markings	X1-X2-X3
Primary Terminals	Pads
Secondary Voltage	575
Secondary Max Current	1004.1A
Secondary Markings	H1-H2-H3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-8
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

1000KVA 480 VOLTS TO 575 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)