

OFFICIAL QUOTE

1000KVA 480 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER





1000KVA 480 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER


\$35,904.00 CAD

Three Phase Autotransformer with a capacity of 1000kVA, transforming 480Y Volts to 120Y Volts

SKU: RA1000H-A

Categories: <u>Autotransformer</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 1000kVA, transforming 480Y Volts to 120Y Volts



OFFICIAL QUOTE





PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	4373 lbs
Phases	<u>3</u>
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	480
Primary Max Current	<u>1202.8A</u>
Primary Markings	H1-H2-H3
Primary Terminals	<u>Pads</u>
Secondary Voltage	120
Secondary Max Current	4811.3A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>2.5 – 4.5%</u>
Sound (db)	64
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-11</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

1000KVA 480 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	<u>Canada/RPM</u>
Country/Manufacturer	<u>Canada/RPM</u>