

OFFICIAL QUOTE

1000KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER





1000KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER


\$20,871.30 CAD


Three Phase Autotransformer with a capacity of 1000kVA, transforming 208Y Volts to 277Y Volts

SKU: RA1000B-D

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 1000kVA, transforming 208Y Volts to 277Y Volts



OFFICIAL QUOTE

1000KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER



PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	1744 lbs
Phases	<u>3</u>
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	208
Primary Max Current	2775.7A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	277
Secondary Max Current	2084.3A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 - 3.0%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-9</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

1000KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------