

OFFICIAL QUOTE

10KVA 200 VOLTS TO 240 VOLTS SINGLE PHASE AUTOTRANSFORMER





10KVA 200 VOLTS TO 240 VOLTS SINGLE PHASE AUTOTRANSFORMER

\$836.40 CAD

Single Phase Autotransformer with a capacity of 10kVA, transforming 200 Volts to 240 Volts

SKU: MC10B1-C

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Autotransformer with a capacity of 10kVA, transforming 200 Volts to 240 Volts



OFFICIAL QUOTE



10KVA 200 VOLTS TO 240 VOLTS SINGLE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	59.9 lbs
Phases	1
kVA	10
Connection	1PhA-NT-1
Primary Voltage	200
Primary Max Current	28.9A
Primary Markings	<u>X0-X1</u>
Primary Terminals	Terminal Blocks
Secondary Voltage	240
Secondary Max Current	24.1A
Secondary Markings	<u>H0-H1</u>
Secondary Terminals	<u>Terminal Blocks</u>
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>0.5 – 1.5%</u>
Sound (db)	40 dB
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-0</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

10KVA 200 VOLTS TO 240 VOLTS SINGLE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------