

OFFICIAL QUOTE

1000KVA 200 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER





1000KVA 200 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER


\$18,840.80 CAD


Three Phase Autotransformer with a capacity of 1000kVA, transforming 200Y Volts to 240Y Volts

SKU: RA1000B1-C

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 1000kVA, transforming 200Y Volts to 240Y Volts



OFFICIAL QUOTE



1000KVA 200 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	1098 lbs
Phases	<u>3</u>
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	200
Primary Max Current	2886.8A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	240
Secondary Max Current	2405.6A
Secondary Markings	H1-H2-H3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 - 1.5%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-8
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

1000KVA 200 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	<u>Canada/RPM</u>
----------------------	-------------------