



## RS40J

**\$771.00 CAD**

SKU: 07717a3bb5b1

Categories: [Motor Starters](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



### PRODUCT SPECIFICATIONS

Weight	80 lbs
Phases	<a href="#">3</a>
HP	<a href="#">40</a>
Enclosure	<a href="#">Core &amp; Coil</a>
Connection	<a href="#">3PhA-ST-0-2</a>
Primary Voltage	<a href="#">600</a>



<b>Primary Max Current</b>	<a href="#">38.5A</a>
<b>Primary Markings</b>	<a href="#">H1-H2-H3</a>
<b>Primary Terminals</b>	<a href="#">Large Scews</a>
<b>Secondary Voltage</b>	<a href="#">65/80/100%</a>
<b>Secondary Max Current</b>	<a href="#">355.3A</a>
<b>Secondary Markings</b>	<a href="#">A-B-C</a>
<b>Secondary Terminals</b>	<a href="#">Large Scews</a>
<b>Primary Taps</b>	<a href="#">N/A</a>
<b>Conductor Material</b>	<a href="#">Copper</a>
<b>Insuation Class</b>	<a href="#">220</a>
<b>BIL (Insulation) Level</b>	<a href="#">10kV</a>
<b>Efficiency</b>	<a href="#">N/A</a>
<b>Impedance</b>	<a href="#">N/A</a>
<b>Sound (db)</b>	<a href="#">N/A</a>
<b>Enclosure Type</b>	<a href="#">N/A</a>