

OFFICIAL QUOTE

1000VA 208 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





1000VA 208 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER


\$471.38 CAD


Single Phase Control Transformer with a capacity of 1000VA, transforming 208 Volts to 120/240 Volts

SKU: CS1000B-K

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 1000VA, transforming 208 Volts to 120/240 Volts



OFFICIAL QUOTE



1000VA 208 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	23 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	208
Primary Max Current	4.81A
Primary Markings	<u>H1-H2</u>
Primary Terminals	<u>Terminals</u>
Secondary Voltage	120/240
Secondary Max Current	8.33A
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	<u>Terminals</u>
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	<u>115°C</u>
Insuation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	5.0 - 7.0%
Sound (db)	40
Enclosure Type	Core & Coil
Enclosure Size	See Core & Coil Chart
Finish/Colour	N/A
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE



1000VA 208 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	1000
Country/Manufacturer	<u>Canada/RPM</u>