



**2000KVA 240 VOLTS TO 200 VOLTS
THREE PHASE AUTOTRANSFORMER**



**2000KVA 240 VOLTS TO
200 VOLTS THREE PHASE
AUTOTRANSFORMER**



\$27,646.10 CAD

Three Phase Autotransformer with a capacity of 2000kVA, transforming 240Y Volts to 200Y Volts

SKU: RA2000C-B1

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 2000kVA, transforming 240Y Volts to 200Y Volts



PRODUCT SPECIFICATIONS

Weight	2058 lbs
Phases	3
kVA	2000
Connection	3PhA-NT-1
Primary Voltage	240
Primary Max Current	4811.3A
Primary Markings	H1-H2-H3
Primary Terminals	Pads
Secondary Voltage	200
Secondary Max Current	5773.5A
Secondary Markings	X1-X2-X3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-10
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

2000KVA 240 VOLTS TO 200 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)