

OFFICIAL QUOTE

300KVA 240 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER





300KVA 240 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER


\$9,091.80 CAD

Three Phase Autotransformer with a capacity of 300kVA, transforming 240Y Volts to 400Y Volts

SKU: RA300C-G1

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 300kVA, transforming 240Y Volts to 400Y Volts



OFFICIAL QUOTE



300KVA 240 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	828 lbs
Phases	<u>3</u>
kVA	300
Connection	3PhA-NT-1
Primary Voltage	240
Primary Max Current	721.7A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	400
Secondary Max Current	<u>433A</u>
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 - 3.0%
Sound (db)	<u>55</u>
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-8</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

300KVA 240 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------