




1000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



1000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



\$37,811.40 CAD

Three Phase Autotransformer with a capacity of 1000kVA, transforming 380Y Volts to 240Y Volts

SKU: RC1000F-C

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 1000kVA, transforming 380Y Volts to 240Y Volts



PRODUCT SPECIFICATIONS

Weight	3078 lbs
Phases	3
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	380
Primary Max Current	1519.3A
Primary Markings	H1-H2-H3
Primary Terminals	Pads
Secondary Voltage	240
Secondary Max Current	2405.6A
Secondary Markings	X1-X2-X3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 – 3.0%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-10
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

1000KVA 380 VOLTS TO 240 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)