



## 1500KVA 120 VOLTS TO 208 VOLTS THREE PHASE AUTOTRANSFORMER

**\$30,380.30 CAD**

Three Phase Autotransformer with a capacity of  
1500kVA, transforming 120Y Volts to 208Y Volts

SKU: RA1500A-B

Categories: [Autotransformer](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 1500kVA, transforming 120Y Volts to 208Y Volts



## PRODUCT SPECIFICATIONS

Weight	4316 lbs
Phases	<a href="#">3</a>
kVA	<a href="#">1500</a>
Connection	<a href="#">3PhA-NT-1</a>
Primary Voltage	<a href="#">120</a>
Primary Max Current	<a href="#">7216.9A</a>
Primary Markings	<a href="#">X1-X2-X3</a>
Primary Terminals	<a href="#">Pads</a>
Secondary Voltage	<a href="#">208</a>
Secondary Max Current	<a href="#">4163.6A</a>
Secondary Markings	<a href="#">H1-H2-H3</a>
Secondary Terminals	<a href="#">Pads</a>
Primary Taps	<a href="#">N/A</a>
Conductor Material	<a href="#">Aluminum</a>
Insulation Class	<a href="#">220°C (Class H)</a>
BIL (Insulation) Level	<a href="#">10kV</a>
Efficiency (@35% Load) %	<a href="#">N/A</a>
Impedance Range	<a href="#">1.5 – 3.5%</a>
Sound (db)	<a href="#">62</a>
Enclosure Type	<a href="#">NEMA 3R Indoor</a>
Enclosure Size	<a href="#">E3R-11</a>
Finish/Colour	<a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>
Standards & Certifications	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a>



OFFICIAL QUOTE

1500KVA 120 VOLTS TO 208 VOLTS  
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	<a href="#">Canada/RPM</a>
----------------------	----------------------------