



**150KVA 480 VOLTS TO 550 VOLTS  
THREE PHASE AUTOTRANSFORMER**



**150KVA 480 VOLTS TO 550  
VOLTS THREE PHASE  
AUTOTRANSFORMER**

**\$3,024.40 CAD**

Three Phase Autotransformer with a capacity of 150kVA, transforming 480Y Volts to 550Y Volts

**SKU:** RC150H-J2

**Categories:** [Autotransformers](#)

**SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**



Three Phase Autotransformer with a capacity of 150kVA, transforming 480Y Volts to 550Y Volts



PRODUCT SPECIFICATIONS

<b>Weight</b>	160 lbs
<b>Phases</b>	<a href="#">3</a>
<b>kVA</b>	<a href="#">150</a>
<b>Connection</b>	<a href="#">3PhA-NT-1</a>
<b>Primary Voltage</b>	<a href="#">480</a>
<b>Primary Max Current</b>	<a href="#">180.4A</a>
<b>Primary Markings</b>	<a href="#">X1-X2-X3</a>
<b>Primary Terminals</b>	<a href="#">300MCM-6</a>
<b>Secondary Voltage</b>	<a href="#">550</a>
<b>Secondary Max Current</b>	<a href="#">157.5A</a>
<b>Secondary Markings</b>	<a href="#">H1-H2-H3</a>
<b>Secondary Terminals</b>	<a href="#">300MCM-6</a>
<b>Primary Taps</b>	<a href="#">N/A</a>
<b>Conductor Material</b>	<a href="#">Copper</a>
<b>Insulation Class</b>	<a href="#">220°C (Class H)</a>
<b>BIL (Insulation) Level</b>	<a href="#">10kV</a>
<b>Efficiency (@35% Load) %</b>	<a href="#">N/A</a>
<b>Impedance Range</b>	<a href="#">0.5 – 1.5%</a>
<b>Sound (db)</b>	<a href="#">45</a>
<b>Enclosure Type</b>	<a href="#">NEMA 3R Indoor</a>
<b>Enclosure Size</b>	<a href="#">E3R-5</a>
<b>Finish/Colour</b>	<a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>
<b>Standards &amp; Certifications</b>	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a>



OFFICIAL QUOTE

150KVA 480 VOLTS TO 550 VOLTS  
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)