



OFFICIAL QUOTE

150KVA 600 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



150KVA 600 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

\$7,725.70 CAD

Three Phase Autotransformer with a capacity of 150kVA, transforming 600Y Volts to 240Y Volts

SKU: RA150J-C

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 150kVA, transforming 600Y Volts to 240Y Volts



OFFICIAL QUOTE

150KVA 600 VOLTS TO 240 VOLTS
THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	595 lbs
Phases	3
kVA	150
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	144.3A
Primary Markings	H1-H2-H3
Primary Terminals	300MCM-6
Secondary Voltage	240
Secondary Max Current	360.8A
Secondary Markings	X1-X2-X3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 – 3.5%
Sound (db)	55
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-8
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

150KVA 600 VOLTS TO 240 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)