



OFFICIAL QUOTE

2000KVA 400 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER



2000KVA 400 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER



\$29,441.30 CAD

Three Phase Autotransformer with a capacity of 2000kVA, transforming 400Y Volts to 277Y Volts

SKU: RA2000G1-D

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 2000kVA, transforming 400Y Volts to 277Y Volts



OFFICIAL QUOTE

2000KVA 400 VOLTS TO 277 VOLTS
THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	4162 lbs
Phases	3
kVA	2000
Connection	3PhA-NT-1
Primary Voltage	400
Primary Max Current	2886.8A
Primary Markings	H1-H2-H3
Primary Terminals	Pads
Secondary Voltage	277
Secondary Max Current	4168.6A
Secondary Markings	X1-X2-X3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 – 3.0%
Sound (db)	62
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-11
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

2000KVA 400 VOLTS TO 277 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)