



OFFICIAL QUOTE

2000KVA 600 VOLTS TO 480 VOLTS THREE PHASE AUTOTRANSFORMER



2000KVA 600 VOLTS TO 480 VOLTS THREE PHASE AUTOTRANSFORMER

\$31,793.00 CAD

Three Phase Autotransformer with a capacity of 2000kVA, transforming 600Y Volts to 480Y Volts

SKU: RA2000J-H

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 2000kVA, transforming 600Y Volts to 480Y Volts



OFFICIAL QUOTE

2000KVA 600 VOLTS TO 480 VOLTS
THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	2538 lbs
Phases	3
kVA	2000
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	1924.5A
Primary Markings	H1-H2-H3
Primary Terminals	Pads
Secondary Voltage	480
Secondary Max Current	2405.6A
Secondary Markings	X1-X2-X3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-10
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

**2000KVA 600 VOLTS TO 480 VOLTS
THREE PHASE AUTOTRANSFORMER**



Country/Manufacturer	Canada/RPM
-----------------------------	----------------------------