



## 30KVA 110 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER

**\$3,061.80 CAD**

Three Phase Autotransformer with a capacity of 30kVA, transforming 110Y Volts to 200Y Volts

SKU: RC30A2-B1

Categories: [Autotransformer](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 110Y Volts to 200Y Volts



## PRODUCT SPECIFICATIONS

Weight	108 lbs
Phases	<a href="#">3</a>
kVA	<a href="#">30</a>
Connection	<a href="#">3PhA-NT-1</a>
Primary Voltage	<a href="#">110</a>
Primary Max Current	<a href="#">157.5A</a>
Primary Markings	<a href="#">X1-X2-X3</a>
Primary Terminals	<a href="#">300MCM-6</a>
Secondary Voltage	<a href="#">200</a>
Secondary Max Current	<a href="#">86.6A</a>
Secondary Markings	<a href="#">H1-H2-H3</a>
Secondary Terminals	<a href="#">#2/0-6 AWG</a>
Primary Taps	<a href="#">N/A</a>
Conductor Material	<a href="#">Copper</a>
Insulation Class	<a href="#">220°C (Class H)</a>
BIL (Insulation) Level	<a href="#">10kV</a>
Efficiency (@35% Load) %	<a href="#">N/A</a>
Impedance Range	<a href="#">1.5 – 3.5%</a>
Sound (db)	<a href="#">45</a>
Enclosure Type	<a href="#">NEMA 3R Indoor</a>
Enclosure Size	<a href="#">E3R-5</a>
Finish/Colour	<a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>
Standards & Certifications	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a>



OFFICIAL QUOTE  
30KVA 110 VOLTS TO 200 VOLTS  
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)