

#### **OFFICIAL QUOTE**

## 30KVA 110 VOLTS TO 550 VOLTS THREE PHASE AUTOTRANSFORMER





### 30KVA 110 VOLTS TO 550 VOLTS THREE PHASE AUTOTRANSFORMER

\$2,761.03 USD

Three Phase Autotransformer with a capacity of 30kVA, transforming 110Y Volts to 550Y Volts

**SKU:** RC30A2-J2

**Categories:** Autotransformer

#### **SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**





Three Phase Autotransformer with a capacity of 30kVA, transforming 110Y Volts to 550Y Volts



### **OFFICIAL QUOTE**



### **PRODUCT SPECIFICATIONS**

Weight	209 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	110
Primary Max Current	<u>157.5A</u>
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	300MCM-6
Secondary Voltage	380
Secondary Max Current	31.5A
Secondary Markings	H1-H2-H3
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>2.5 – 4.5%</u>
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-6</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



### **OFFICIAL QUOTE**

# 30KVA 110 VOLTS TO 550 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------