



OFFICIAL QUOTE

30KVA 110 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER



30KVA 110 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER

\$3,779.90 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 110Y Volts to 600Y Volts

SKU: RC30A2-J

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 110Y Volts to 600Y Volts



OFFICIAL QUOTE

30KVA 110 VOLTS TO 600 VOLTS
THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	214 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	110
Primary Max Current	157.5A
Primary Markings	X1-X2-X3
Primary Terminals	300MCM-6
Secondary Voltage	600
Secondary Max Current	28.9A
Secondary Markings	H1-H2-H3
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	2.5 – 4.5%
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-6
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 110 VOLTS TO 600 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)