


OFFICIAL QUOTE

30KVA 115 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER





30KVA 115 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER


\$2,891.70 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 115Y Volts to 200Y Volts

SKU: RC30A1-B1

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 30kVA, transforming 115Y Volts to 200Y Volts



OFFICIAL QUOTE 30KVA 115 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	101 lbs
Phases	<u>3</u>
kVA	30
Connection	3PhA-NT-1
Primary Voltage	115
Primary Max Current	<u>150.6A</u>
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	300MCM-6
Secondary Voltage	200
Secondary Max Current	86.6A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	#2/0-6 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 - 3.5%
Sound (db)	<u>45</u>
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-5</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 115 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------