


OFFICIAL QUOTE

30KVA 115 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER





30KVA 115 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER


\$3,516.60 CAD


Three Phase Autotransformer with a capacity of 30kVA, transforming 115Y Volts to 600Y Volts

SKU: RA30A1-J

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 30kVA, transforming 115Y Volts to 600Y Volts



OFFICIAL QUOTE



30KVA 115 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	158 lbs
Phases	<u>3</u>
kVA	30
Connection	3PhA-NT-1
Primary Voltage	115
Primary Max Current	150.6A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	300MCM-6
Secondary Voltage	600
Secondary Max Current	28.9A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	2.5 - 4.5%
Sound (db)	<u>45</u>
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-6</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 115 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	<u>Canada/RPM</u>
----------------------	-------------------