




OFFICIAL QUOTE

30KVA 208 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



30KVA 208 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



\$1,615.00 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 208Y Volts to 240Y Volts

SKU: RC30B-C

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 208Y Volts to 240Y Volts



OFFICIAL QUOTE

30KVA 208 VOLTS TO 240 VOLTS
THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	27 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	208
Primary Max Current	83.3A
Primary Markings	X1-X2-X3
Primary Terminals	#2/0-6 AWG
Secondary Voltage	240
Secondary Max Current	72.2A
Secondary Markings	H1-H2-H3
Secondary Terminals	#2-14 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	E1-1
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

**30KVA 208 VOLTS TO 240 VOLTS
THREE PHASE AUTOTRANSFORMER**



Country/Manufacturer	Canada/RPM
-----------------------------	----------------------------