

OFFICIAL QUOTE

30KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER





30KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,595.40 CAD


Three Phase Autotransformer with a capacity of 30kVA, transforming 220Y Volts to 200Y Volts

SKU: RC30C2-B1

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 30kVA, transforming 220Y Volts to 200Y Volts



OFFICIAL QUOTE





PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	20 lbs
Phases	<u>3</u>
kVA	<u>30</u>
Connection	<u>3PhA-NT-1</u>
Primary Voltage	220
Primary Max Current	<u>78.7A</u>
Primary Markings	H1-H2-H3
Primary Terminals	#2/0-6 AWG
Secondary Voltage	200
Secondary Max Current	86.6A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	#2/0-6 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>0.5 – 1.5%</u>
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
,	