



30KVA 220 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER

\$2,864.80 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 220Y Volts to 380Y Volts

SKU: RC30C2-F

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 220Y Volts to 380Y Volts



PRODUCT SPECIFICATIONS

| | |
|----------------------------|--|
| Weight | 100 lbs |
| Phases | 3 |
| kVA | 30 |
| Connection | 3PhA-NT-1 |
| Primary Voltage | 220 |
| Primary Max Current | 78.7A |
| Primary Markings | X1-X2-X3 |
| Primary Terminals | #2/0-6 AWG |
| Secondary Voltage | 380 |
| Secondary Max Current | 45.6A |
| Secondary Markings | H1-H2-H3 |
| Secondary Terminals | #2-14 AWG |
| Primary Taps | N/A |
| Conductor Material | Copper |
| Insulation Class | 220°C (Class H) |
| BIL (Insulation) Level | 10kV |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | 1.5 – 3.5% |
| Sound (db) | 45 |
| Enclosure Type | NEMA 3R Indoor |
| Enclosure Size | E3R-5 |
| Finish/Colour | Polyester Powder Coat – ANSI/ASA 61 Grey |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered |



OFFICIAL QUOTE

30KVA 220 VOLTS TO 380 VOLTS

THREE PHASE AUTOTRANSFORMER



| | |
|----------------------|----------------------------|
| Country/Manufacturer | Canada/RPM |
|----------------------|----------------------------|