



30KVA 240 VOLTS TO 220 VOLTS THREE PHASE AUTOTRANSFORMER



\$1,517.60 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 240Y Volts to 220Y Volts

SKU: RC30C-C2

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 240Y Volts to 220Y Volts



PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	240
Primary Max Current	72.2A
Primary Markings	H1-H2-H3
Primary Terminals	#2-14 AWG
Secondary Voltage	220
Secondary Max Current	78.7A
Secondary Markings	X1-X2-X3
Secondary Terminals	#2/0-6 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	E1-1
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 240 VOLTS TO 220 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	----------------------------