



**30KVA 240 VOLTS TO 380 VOLTS
THREE PHASE AUTOTRANSFORMER**



**30KVA 240 VOLTS TO 380
VOLTS THREE PHASE
AUTOTRANSFORMER**

\$2,506.70 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 240Y Volts to 380Y Volts

SKU: RC30C-F

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 240Y Volts to 380Y Volts



PRODUCT SPECIFICATIONS

Weight	86 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	240
Primary Max Current	72.2A
Primary Markings	X1-X2-X3
Primary Terminals	#2-14 AWG
Secondary Voltage	380
Secondary Max Current	45.6A
Secondary Markings	H1-H2-H3
Secondary Terminals	#2-14 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 – 3.0%
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-5
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 240 VOLTS TO 380 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	----------------------------