



30KVA 380 VOLTS TO 220 VOLTS THREE PHASE AUTOTRANSFORMER


\$2,864.80 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 380Y Volts to 220Y Volts

SKU: RC30F-C2

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 380Y Volts to 220Y Volts



PRODUCT SPECIFICATIONS

Weight	100 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	380
Primary Max Current	45.6A
Primary Markings	H1-H2-H3
Primary Terminals	#2-14 AWG
Secondary Voltage	220
Secondary Max Current	78.7A
Secondary Markings	X1-X2-X3
Secondary Terminals	#2/0-6 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 – 3.5%
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-5
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 380 VOLTS TO 220 VOLTS

THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	----------------------------