



30KVA 400 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,237.50 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 400Y Volts to 380Y Volts

SKU: RC30G1-F

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 30kVA, transforming 400Y Volts to 380Y Volts



PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	400
Primary Max Current	43.3A
Primary Markings	H1-H2-H3
Primary Terminals	#2-14 AWG
Secondary Voltage	380
Secondary Max Current	45.6A
Secondary Markings	X1-X2-X3
Secondary Terminals	#2-14 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	E1-1
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE
30KVA 400 VOLTS TO 380 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	----------------------------