

OFFICIAL QUOTE

30KVA 550 VOLTS TO 480 VOLTS THREE PHASE AUTOTRANSFORMER





30KVA 550 VOLTS TO 480 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,576.40 CAD

Three Phase Autotransformer with a capacity of 30kVA, transforming 550Y Volts to 480Y Volts

SKU: RC30J2-H

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 30kVA, transforming 550Y Volts to 480Y Volts



OFFICIAL QUOTE



30KVA 550 VOLTS TO 480 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	25 lbs
Phases	<u>3</u>
kVA	30
Connection	<u>3PhA-NT-1</u>
Primary Voltage	<u>550</u>
Primary Max Current	31.5A
Primary Markings	H1-H2-H3
Primary Terminals	Terminal Blocks
Secondary Voltage	480
Secondary Max Current	<u>36.1A</u>
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	#2-14 AWG
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 - 1.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 550 VOLTS TO 480 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------