



## OFFICIAL QUOTE

### 37.5KVA 550 VOLTS TO 110 VOLTS SINGLE PHASE AUTOTRANSFORMER



## 37.5KVA 550 VOLTS TO 110 VOLTS SINGLE PHASE AUTOTRANSFORMER


**\$4,218.50 CAD**

Single Phase Autotransformer with a capacity of 37.5kVA, transforming 550 Volts to 110 Volts

SKU: MC37J2-A2

Categories: [Autotransformers](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Single Phase Autotransformer with a capacity of 37.5kVA, transforming 550 Volts to 110 Volts



## OFFICIAL QUOTE

37.5KVA 550 VOLTS TO 110 VOLTS  
SINGLE PHASE AUTOTRANSFORMER

## PRODUCT SPECIFICATIONS

|                            |                                                                                                      |
|----------------------------|------------------------------------------------------------------------------------------------------|
| Weight                     | 266 lbs                                                                                              |
| Phases                     | <a href="#">1</a>                                                                                    |
| kVA                        | <a href="#">37.5</a>                                                                                 |
| Connection                 | <a href="#">1PhA-NT-1</a>                                                                            |
| Primary Voltage            | <a href="#">550</a>                                                                                  |
| Primary Max Current        | <a href="#">39.4A</a>                                                                                |
| Primary Markings           | <a href="#">H0-H1</a>                                                                                |
| Primary Terminals          | <a href="#">#2-14 AWG</a>                                                                            |
| Secondary Voltage          | <a href="#">110</a>                                                                                  |
| Secondary Max Current      | <a href="#">196.8A</a>                                                                               |
| Secondary Markings         | <a href="#">X0-X1</a>                                                                                |
| Secondary Terminals        | <a href="#">600MCM-2</a>                                                                             |
| Primary Taps               | <a href="#">N/A</a>                                                                                  |
| Conductor Material         | <a href="#">Copper</a>                                                                               |
| Insulation Class           | <a href="#">220°C (Class H)</a>                                                                      |
| BIL (Insulation) Level     | <a href="#">10kV</a>                                                                                 |
| Efficiency (@35% Load) %   | <a href="#">N/A</a>                                                                                  |
| Impedance Range            | <a href="#">2.5 – 4.5%</a>                                                                           |
| Sound (db)                 | <a href="#">45 dB</a>                                                                                |
| Enclosure Type             | <a href="#">NEMA 3R Indoor</a>                                                                       |
| Enclosure Size             | <a href="#">E3R-6</a>                                                                                |
| Finish/Colour              | <a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>                                             |
| Standards & Certifications | <a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a> |



## OFFICIAL QUOTE

**37.5KVA 550 VOLTS TO 110 VOLTS  
SINGLE PHASE AUTOTRANSFORMER**



|                             |                            |
|-----------------------------|----------------------------|
| <b>Country/Manufacturer</b> | <a href="#">Canada/RPM</a> |
|-----------------------------|----------------------------|