

OFFICIAL QUOTE

3KVA 110 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER





3KVA 110 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER


\$1,500.50 CAD

Three Phase Autotransformer with a capacity of 3kVA, transforming 110Y Volts to 600Y Volts

SKU: RC3A2-J

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 3kVA, transforming 110Y Volts to 600Y Volts



OFFICIAL QUOTE



3KVA 110 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	3
Connection	<u>3PhA-NT-1</u>
Primary Voltage	110
Primary Max Current	<u>15.7A</u>
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	Terminal Blocks
Secondary Voltage	600
Secondary Max Current	2.9A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>2.5 – 4.5%</u>
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

3KVA 110 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------