



3KVA 120 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,129.50 CAD

Three Phase Autotransformer with a capacity of 3kVA, transforming 120Y Volts to 200Y Volts

SKU: RC3A-B1

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 3kVA, transforming 120Y Volts to 200Y Volts



PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	3
Connection	3PhA-NT-1
Primary Voltage	120
Primary Max Current	14.4A
Primary Markings	X1-X2-X3
Primary Terminals	Terminal Blocks
Secondary Voltage	200
Secondary Max Current	8.7A
Secondary Markings	H1-H2-H3
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 – 3.0%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	E1-1
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE
3KVA 120 VOLTS TO 200 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)