

#### **OFFICIAL QUOTE**

### 3KVA 120 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER





# 3KVA 120 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,004.99 USD

Three Phase Autotransformer with a capacity of 3kVA, transforming 120Y Volts to 380Y Volts

SKU: RC3A-F

**Categories:** Autotransformer

#### **SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**





Three Phase Autotransformer with a capacity of 3kVA, transforming 120Y Volts to 380Y Volts



#### **OFFICIAL QUOTE**

## 3KVA 120 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER



#### **PRODUCT SPECIFICATIONS**

Weight	20 lbs
Phases	<u>3</u>
kVA	<u>3</u>
Connection	3PhA-NT-1
Primary Voltage	120
Primary Max Current	14.4A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	Terminal Blocks
Secondary Voltage	380
Secondary Max Current	4.6A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	2.5 - 4.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



#### **OFFICIAL QUOTE**

## 3KVA 120 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------