



OFFICIAL QUOTE

600KVA 416 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER



600KVA 416 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER



\$16,193.80 CAD

Three Phase Autotransformer with a capacity of 600kVA, transforming 416Y Volts to 600Y Volts

SKU: RA600G-J

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 600kVA, transforming 416Y Volts to 600Y Volts



OFFICIAL QUOTE

600KVA 416 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER



PRODUCT SPECIFICATIONS

Weight	1231 lbs
Phases	3
kVA	600
Connection	3PhA-NT-1
Primary Voltage	416
Primary Max Current	832.7A
Primary Markings	X1-X2-X3
Primary Terminals	Pads
Secondary Voltage	600
Secondary Max Current	577.4A
Secondary Markings	H1-H2-H3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 – 3.0%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-9
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

600KVA 416 VOLTS TO 600 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

[Canada/RPM](#)