

OFFICIAL QUOTE

6KVA 110 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER





6KVA 110 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,586.00 CAD


Three Phase Autotransformer with a capacity of 6kVA, transforming 110Y Volts to 200Y Volts

SKU: RC6A2-B1

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 6kVA, transforming 110Y Volts to 200Y Volts



OFFICIAL QUOTE 6KVA 110 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	<u>6</u>
Connection	<u>3PhA-NT-1</u>
Primary Voltage	110
Primary Max Current	31.5A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	<u>Terminal Blocks</u>
Secondary Voltage	200
Secondary Max Current	<u>17.3A</u>
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>1.5 - 3.5%</u>
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

6KVA 110 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------