

OFFICIAL QUOTE

6KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER





6KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER


\$1,235.60 CAD

Three Phase Autotransformer with a capacity of 6kVA, transforming 208Y Volts to 277Y Volts

SKU: RC6B-D

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 6kVA, transforming 208Y Volts to 277Y Volts



OFFICIAL QUOTE



6KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	20 lbs
Phases	<u>3</u>
kVA	<u>6</u>
Connection	3PhA-NT-1
Primary Voltage	208
Primary Max Current	<u>16.7A</u>
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	<u>Terminal Blocks</u>
Secondary Voltage	277
Secondary Max Current	12.5A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 - 3.0%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

6KVA 208 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------