

OFFICIAL QUOTE

6KVA 208 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER





6KVA 208 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,591.40 CAD

Three Phase Autotransformer with a capacity of 6kVA, transforming 208Y Volts to 380Y Volts

SKU: RC6B-F Categories: <u>Autotransformer</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 6kVA, transforming 208Y Volts to 380Y Volts



OFFICIAL QUOTE

6KVA 208 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER



PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	<u>3</u>
kVA	<u>6</u>
Connection	<u>3PhA-NT-1</u>
Primary Voltage	<u>208</u>
Primary Max Current	<u>16.7A</u>
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	Terminal Blocks
Secondary Voltage	380
Secondary Max Current	<u>9.1A</u>
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Insulation Class	<u>180°C (Class F)</u>
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	<u>N/A</u>
Impedance Range	<u>1.5 – 3.5%</u>
Sound (db)	<u>40</u>
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	<u>CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015</u> <u>Registered</u>



OFFICIAL QUOTE

6KVA 208 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

Canada/RPM