

OFFICIAL QUOTE

6KVA 220 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER





6KVA 220 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,595.40 CAD

Three Phase Autotransformer with a capacity of 6kVA, transforming 220Y Volts to 120Y Volts

SKU: RC6C2-A

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 6kVA, transforming 220Y Volts to 120Y Volts



OFFICIAL QUOTE

QUOTE TO 120 VOLTS OTRANSFORMER

6KVA 220 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	<u>6</u>
Connection	<u>3PhA-NT-1</u>
Primary Voltage	220
Primary Max Current	<u>15.7A</u>
Primary Markings	H1-H2-H3
Primary Terminals	Terminal Blocks
Secondary Voltage	120
Secondary Max Current	28.9A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 - 3.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

6KVA 220 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------