

OFFICIAL QUOTE

6KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER





6KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER


\$893.90 CAD

Three Phase Autotransformer with a capacity of 6kVA, transforming 220Y Volts to 200Y Volts

SKU: RC6C2-B1

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 6kVA, transforming 220Y Volts to 200Y Volts



OFFICIAL QUOTE



6KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	20 lbs
Phases	3
kVA	<u>6</u>
Connection	3PhA-NT-1
Primary Voltage	220
Primary Max Current	15.7A
Primary Markings	H1-H2-H3
Primary Terminals	Terminal Blocks
Secondary Voltage	200
Secondary Max Current	17.3A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 – 1.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

6KVA 220 VOLTS TO 200 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------