

#### **OFFICIAL QUOTE**

# 6KVA 230 VOLTS TO 208 VOLTS THREE PHASE AUTOTRANSFORMER





## 6KVA 230 VOLTS TO 208 VOLTS THREE PHASE AUTOTRANSFORMER


\$665.84 USD

Three Phase Autotransformer with a capacity of 6kVA, transforming 230Y Volts to 208Y Volts

SKU: RC6C1-B

**Categories:** Autotransformer

#### **SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**





Three Phase Autotransformer with a capacity of 6kVA, transforming 230Y Volts to 208Y Volts



### **OFFICIAL QUOTE**





#### PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	20 lbs
Phases	<u>3</u>
kVA	<u>6</u>
Connection	3PhA-NT-1
Primary Voltage	230
Primary Max Current	15.1A
Primary Markings	H1-H2-H3
Primary Terminals	Terminal Blocks
Secondary Voltage	208
Secondary Max Current	16.7A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 - 1.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-1</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



### **OFFICIAL QUOTE**

# 6KVA 230 VOLTS TO 208 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------